

Sticklers™ Fiber Optic Splice & Connector Cleaner II Cleaning Fluid



Product Features:

- Fast evaporating, no residue optical grade cleaning fluid for cleaning fiber
- Not regulated for easy transport by land, sea or air
- · Nonflammable, nontoxic
- · Dissipates electrostatic charges
- Compliant with Ventura County Air Pollution Control District Rule 74.6; reference 74.6; B.2.C
- · ROHS and REACH compliant



Triton™ Cap for Flexible Dispensing

High Purity Precision Valve

Non-pressurized, Hermetically Sealed Can

Multilingual Label



3 oz can (MCC-SFOC03M) comes in hassle-free travel size packaging.

TYPICAL CLEANING APPLICATIONS:

Pigtails and bare fibers for fusion splicing

Ribbon fibers for mass fusion splicing

Splicing plastic optical fibers and connectors

Ceramic and composite ferrules

Most glass and plastic photonic lenses

Suitable cleaning fluid for tool kits



Patented Triton™
dispenser enables
3 cleaning methods



How to Use Fiber Optic Splice & Connector Cleaner @ SticklersCleaners.com

PACKAGING:	3 OZ (85 G) NET FLUID WEIGHT	10 OZ (284 G) NET FLUID WEIGHT	
Part Number	MCC-SFOC03M Travel Safe	MCC-SFOC10M	
Cleans Per Can	650+	2500+	
Can Specifications	 4.23 oz (120 g) total can weight 1.54" OD x 5.12" H (39 mm OD x 130 mm H) 	 13.2 oz (374 g) total can weight 2.6" OD x 6.75" H (66 mm OD x 172 mm H) 	
Case Dimensions	8" L x 6" W x 6" H (203 mm L x 152 mm W x 152 mm H)	12" L x 9" W x 7" H (305 mm L x 229 mm W x 178 mm H)	
Case Quantity	12 Cans per Case	12 Cans per Case	
GHS/HCS Pictogram	◆	()	
Recycle Symbol	40\ FE	40\ FE	



Sticklers™ Fiber Optic Splice & Connector Cleaner II conforms to the following Fiber Optic Industry Standards:

INDUSTRY STANDARDS	SECTION	DESCRIPTION
ANSI/TIA 455-240 2009		Fiber Optic Connector End-Face Cleaning Evaluation
ANSI/TIA 568.3D-2016	E.3.5	Connector End-Face Cleaning
ARINC 805-4		Fiber Optic Test Procedures
ARINC 806-5		Fiber Optic Installation & Maintenance
AT&T ATT-TP-76461		Inspecting & Cleaning End-Faces
Cisco Systems Doc: 51837		Inspecting & Cleaning Procedures for Fiber Connectors
IBM SY27-2597-15		Cleaning End-Faces for Maintaining Fiber Links
IEC 61300-3-35	5.3	End-Face Cleaning
IEC 61627-1	7.8	Acceptable Wet-Dry End-Face Cleaning
IEC 62627-1	9.3	Procedure Wet-Dry Cleaning w/ Reel Type Cleaners
IEC 61627-1	9.4	Procedure Wet-Dry Cleaning w/ Sticks & Clickers
IPC 8497-1	7.3.6	Cleaning Fluids & West Swabs & Face Cleaning
IPC 8497-1	10	Minimizing Electrostatic Charge Effect
NASA-STD 8739.5A	8	Cleaning Workmanship Standards
SAE AIR6031		End-Face Cleaning
SAE ARP 6283	8.6	Approved Cleaning Solvents
SAE ARP 6283	9.1.1	Wet-Dry Cassette Cleaning
Telcordia GR2923 CORE Issue 2		End-Face Cleaning
Telcordia GR765-CORE	4.6	Fusion Splicing Materials & Consumables Criteria
Verizon VZ.TRP.9461	5.0	End-Face Cleaning

When You Need Perfectly Clean Splices & Connectors™



SticklersCleaners.com





MicroCare, LLC

595 John Downey Drive New Britain, CT 06051 USA Tel: +1 860 827 0626 Toll Free: 1 800 638 0125

MicroCare U.K. Ltd Unit 4, Whitehall Court

Leeds LS12 5SN UK Tel: +44 (0) 113 3609019

MicroCare Asia Pte Ltd

102E, Pasir Panjang Road Citilink, #05-06 Singapore 118529 Tel: +65 6271 0182

Email: TechSupport@MicroCare.sg



For more information and to download SDS visit our website: SticklersCleaners.com